

# 13.9kVA Pramac 3 Phase Silenced Generator (P12000-3PH)

The Pramac P12000-3PH is a powerful and reliable three-phase petrol generator designed for applications where low noise levels are essential. Its quiet operation makes it ideal for residential areas, commercial environments, and use outside normal working hours.

Powered by a dependable petrol engine and built with first-class components, the P12000-3PH delivers reliable performance when you need dependable power. The generator features comprehensive instrumentation for easy monitoring and operation.



## THE SILENT POWER

### FEATURES

- Low noise level
- Quiet operation – 61dB
- Electric Start
- Brushless
- Genset Control Panels

### Standard Equipment

- Prewired for remote control #AVR #CONN
- Differential protection #DPP

### Optional Accessories using CONN connector

- 2 Wire remote start controller
- Wireless remote start/stop
- AMF (Automatic mains failure)

#### MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

#### SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 8048

#### BRISBANE

1 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6344

#### PERTH

1/85 Dixon Road  
Rockingham, WA 6168  
(08) 9548 7337

# Specifications

| Model                  | P12000-3PH         |
|------------------------|--------------------|
| Frequency              | 50Hz               |
| Voltage                | 400/230V           |
| Power Factor           | 0.8                |
| Standby Power LTP      | 13.9kVA            |
| Continuous Power COP   | 11.8kVA            |
| Engine Manufacturer    | Honda GX630        |
| Starting System        | Electric           |
| Aspiration             | Natural            |
| Fuel                   | Petrol             |
| Weight                 | 188kg              |
| Dimensions (L x W x H) | 990 x 602 x 826 mm |
| Fuel Tank Capacity     | 24L                |
| Noise Level (dB @ 7m)  | 61dB               |
| Phase                  | 3                  |

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949



POWER ANYWHERE, ANYTIME!

**1300 MAC GEN (1300 622 436)**

[www.macfarlanegenerators.com.au](http://www.macfarlanegenerators.com.au)

[info@macgen.com](mailto:info@macgen.com)

## MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

## SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 8048

## BRISBANE

1 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6344

## PERTH

1/85 Dixon Road  
Rockingham, WA 6168  
(08) 9548 7337