

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE
GENERATORS**

ESTABLISHED 1949



4.2kVA Pramac Petrol Generator (PX5000)

ENGINEERED FOR PROFESSIONAL PERFORMANCE

Pramac introduces the PX series, engineered and designed for a professional performance. Ready to move where power is needed, and configured with a strong and compact frame with integrated handle and wheels, that allows to transport it easily.

All parts of the PX generators have been thought to give a long lasting professional generator, with a low noise emission to guarantee the best working conditions. The control panel has been configured to put at your disposal the right outputs, controls and information. Its digital display shows, with the touch of a button, working hours, Hertz and volts.

The PX Series gives you the best power for professional tools.

**COMPACT
EFFICIENT
DURABLE**



FEATURES

- Compliant to the Noise level in Europe
- Automatic Voltage Regulator
- Digital 3 Function Control panel
- Low Noise Emission
- Steel tank and Roll cage design
- Folding handle with foam
- Wheel kit assembled - easy to move
- 3 Years Limited Warranty



MELBOURNE

136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY

1 St James Place
Seven Hills, NSW 2147
(02) 9899 8048

BRISBANE

1 South Pine Road
Brendale, QLD 4500
(07) 3205 6344

PERTH

26 Allambi Way
South Yunderup, WA 6208
0418 931 718

Specifications

Model	PX5000
Frequency	50Hz
Voltage	230V
Power Factor	0.9
Phase	1
Standby Power LTP	4.2kVA
Continuous Power COP	3.9kVA
Engine Manufacturer	SR188F
Starting System	Recoil
Aspiration	Natural
Fuel	Petrol
Weight	79kg
Dimensions (L x W x H)	727 x 515 x 670 mm
Fuel Tank Capacity	27L
Fuel Consumption @100% PRP	1.92 l/h
Running Time @100% PRP	14.06 h
Noise Level (dB @ 7m)	69dB
Manufacturers Warranty Which ever occurs first	Domestic - 3 years or 225 operation hrs
	Commercial - 1 year or 500 operation hrs

Disclaimer: Every effort has been made to publish the correct details in this brochure. No responsibility will be taken for errors, omissions or changes in product specifications. Recommend contacting your local branch on 1300 MAC GEN (1300 622 436) to confirm the suitability of products for your needs.

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE
GENERATORS**

ESTABLISHED 1949

POWER ANYWHERE, ANYTIME!

1300 MAC GEN (1300 622 436)

www.macfarlanegenerators.com.au

info@macgen.com

MELBOURNE

136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY

1 St James Place
Seven Hills, NSW 2147
(02) 9899 8048

BRISBANE

1 South Pine Road
Brendale, QLD 4500
(07) 3205 6344

PERTH

26 Allambi Way
South Yunderup, WA 6208
0418 931 718