

4.2kVA Pramac Petrol Inverter Generator

Pramac PMi inverter generators offer quiet, reliable power for your outdoor power needs: power your camping, tailgating, and your leisure time with a brand new inverter!

The Pramac PMi4500 offers an optimal balance of silent operation, fuel efficiency, and voltage stability. Thanks to advanced inverter technology, these generators stabilise output voltage to deliver clean, reliable power for all types of equipment, from sensitive electronics to demanding tools.

With smart engine speed adjustment based on the required load, the PMi4500 significantly reduces average fuel consumption while maximising efficiency.

Compact, Quiet, and Dependable, they are the ideal solution for both professional and recreational use.

-  • PORTABILITY
-  • DURABILITY
-  • LOW NOISE
-  • USB
-  • RECOIL AND ELECTRIC START
-  • DIRECT CURRENT



FEATURES

- Inverter Technology
- Pramac OHV Engine
- Integrated USB Ports
- Quiet - 68dB
- Low Oil Level Shutdown
- Economy Mode
- 3 Years Limited Warranty



MELBOURNE
136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY
1 St James Place
Seven Hills, NSW 2147
(02) 9899 8048

BRISBANE
1 South Pine Road
Brendale, QLD 4500
(07) 3205 6344

PERTH
26 Allambi Way
South Yunderup, WA 6208
0418 931 718

Specifications

Model	PMi4500
Frequency	50Hz
Voltage	230V
Displacement	224 cc
Phase	1
Max Power	4200W
Rated Power	3800W
Engine Manufacturer	Pramac OHV
Starting System	Electric (+Recoil) 2 wire auto start
Fuel	Petrol
Sockets	2 x 15 amp outlets 1 x DC 12V 6A
Weight	42.5kg
Dimensions (LWH)	578 x 422 x 500 mm
Fuel Tank Capacity	12 L
Fuel Consumption @50%	1.20 l/h
Running Time @50% Load	9.7 hrs Eco mode
Noise Level (dB @ 7m)	68dB(A)
Manufacturers Warranty	Domestic - 3 years or 225 operation hrs
Which ever occurs first	Commercial - 1 year or 500 operation hrs

Disclaimer: Every effort has been made to publish the correct details in this brochure. No responsibility will be taken for errors, omissions or changes in product specifications. Recommend contacting your local branch on 1300 MAC GEN (1300 622 436) to confirm the suitability of products for your needs.



POWER ANYWHERE, ANYTIME!

1300 MAC GEN (1300 622 436)

www.macfarlanegenerators.com.au

info@macgen.com

2

MELBOURNE

136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY

1 St James Place
Seven Hills, NSW 2147
(02) 9899 8048

BRISBANE

1 South Pine Road
Brendale, QLD 4500
(07) 3205 6344

PERTH

26 Allambi Way
South Yunderup, WA 6208
0418 931 718