

3.3kW INVERTER GENERATOR

A quiet, fuel-efficient and modern OHV four-stroke engine powers the enclosed range of Kompak Inverter Technology generators. Long run time and Low sound emissions (complying with National Parks requirements) make these power packs ideal for your RV or camping trip or running your sensitive electronic equipment.

DESCRIPTION / DISCRIBIR	GENERATOR MODEL	KGG3300SEi
	REFERENCE	
GENERATOR SET / GENERADOR LISTO	RATED POWER (w)	3100
	MAX. POWER (w)	3300
	FREQUENCY (Hz)	50
	VOLTAGE (V)	240 v
	CURRENT (A)	13,75
	SOCKETS	Twin outlets
	DISPLAY	yes
	BATTERY (Ah)	yes
	FUEL TANK CAPACITY (L)	6 L
	DC OUTPUT (V) / INTENSITY (A)	12V / 8.3A
	RUNNING TIME UNDER (h 50/100% loading)	5-4 hrs
	NOISE LEVEL @7 METERS (dBA)	58 dB(A)
ENGINE / MOTOR	ENGINE MODEL	XG157F
	IGNITION SYSTEM	C.D.I.
	SPEED REGULATION	Electronic
	STARTING METHOD	Electric / Remote start
	DISPLACEMENT (cc)	149 cc
	OIL CAPACITY (L)	0.45 L
ALTERNATOR / ALTERNADOR	ALTERNATOR	Inverter
	RATED POWER (kW/kVA)	3.3
	POWER FACTOR (Cosφ)	1
	VOLTAGE REGULATION	Digital
ALARMS / ALARMAS	LOW OIL LEVEL	YES
	OVERLOAD INDICATOR	YES
	EMERGENCY STOP	NO
WEIGHT / PESO	WEIGHT (kg)	30
	DIMENSIONS (mm)	555 x 340 x 500 mm

GENERATOR SET / GENERADOR LISTO



ACCESSORIES - TROLLEY

