

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

**MAXWATT**<sup>TM</sup>  
POWER WHEN YOU NEED IT

**MX6000iS**

# 6.3kVA Maxwatt Pure Sine Wave Digital Inverter Generator

2 WIRE AUTO START


LOW NOISE 63DB | ECONOMY LOW IDLE SETTING

Maxwatt® digital inverter generators offer the best in portable power, fuel efficiency and are super silent.


Maxwatt MX6000iS petrol digital inverter generator with electric start offers the best in portable power and fuel efficiency and is super silent. It has a 2-wire auto-start to provide backup power for off-grid solar power systems. Besides the electrical output being able to power all sensitive equipment, the MX6000iS is perfect for recreational caravanning and camping and also useful for home use as a backup power supply.



PUSH BUTTON/  
RECOIL START




TELESCOPIC  
HANDLE



SOLAR  
OFF GRID  
READY

**DOUBLE  
POWER**  
WITH PARALLEL  
CONNECTIVITY



Remote  
Control Start

Li-ION Battery



2  
YEAR  
WARRANTY



Double your power by connecting  
2 generators in parallel

## FEATURES

- IP66 Weatherproof Outlet
- Low Noise at 63dB
- 5V 2.1 Amp USB Outlet
- Parallel Connection Cable included
- Smart Engine Control
- Ideal for Home/Camping/Caravanning

### MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

### SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 8048

### BRISBANE

1 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6344

### PERTH

1/85 Dixon Road  
Rockingham, WA 6168  
(08) 9548 7337

# Specifications

Model	MX6000iS
Power Maximum	6300W
Power Rated	6000W
Voltage	240V
Amperage	22.9A
Outlets	1 x 32 Amp, 1 x 15 Amp IPP Socket
Displacement	322cc
Ignition	Remote / Electric / Recoil / 2 Wire Auto
Battery Charger	Yes
Rated Frequency	50Hz
Cont. Running Time @50% Load	9.8hrs
Cont. Running Time @100% Load	5.5hrs
Fuel Tank Capacity	13.5L
Noise Level (dB @ 75% m)	63
Total harmonic distortion (THD)	3%
Weight (kg)	57kg
Dimensions (LWH)	638 x 499 x 543mm
Manufacturer's Warranty	2 year warranty

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

**POWER ANYWHERE, ANYTIME!**  
**1300 MAC GEN (1300 622 436)**  
**[www.macfarlanegenerators.com.au](http://www.macfarlanegenerators.com.au)**  
**[info@macgen.com](mailto:info@macgen.com)**

## MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

## SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 8048

## BRISBANE

1 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6344

## PERTH

1/85 Dixon Road  
Rockingham, WA 6168  
(08) 9548 7337