



6kVA Maxwatt Pure Sine Wave Digital Inverter Generator

PORTABLE & LIGHT WEIGHT LOW NOISE 63DB | ECONOMY LOW IDLE SETTING

Maxwatt®digital inverter generators offer the best in portable power,

fuel efficiency and are super silent.

MaxWatt MX6000iS Petrol digital inverter generator with electric start offers the best in portable power and fuel efficiency and is super silent. Besides the electrical output being able to power all sensitive equipment, the MX6000iS is perfect for recreational caravanning and camping and also useful for home use as a backup power supply.



















Double your power by connecting 2 generators in parallel

FEATURES

- IP66 Weatherproof Outlet
- Low Noise at 63dB
- 5V 2.1 Amp USB Outlet
- Parallel Connection Cable included
- Smart Engine Control
- Ideal for Home/Camping/Caravanning

MELBOURNE

136 Fairbank Road Clayton South, VIC 3169 (03) 9544 4222

SYDNEY

1 St James Place Seven Hills, NSW 2147 (02) 9899 6699

BRISBANE

31 South Pine Road Brendale, QLD 4500 (07) 3205 6333

Specifications

Model	MX6000iS
Power Maximum	6000W
Power Rated	5500W
Voltage	240V
Amperage	22.9A
Outlets	1 x 32 Amp, 1 x 15 Amp IPP Socket
Displacement	322cc
Ignition	Remote / Electric / Recoil Start
Rated Frequency	50Hz
Cont. Running Time @50% Load	9.8hrs
Cont. Running Time @100% Load	5.5hrs
Fuel Tank Capacity	13.5L
Noise Level (dB @ 75% m)	63
Total harmonic distortion (THD)	3%
Weight (kg)	57kg
Dimensions (LWH)	638 x 499 x 543mm
Manufacturer's Warranty	2 year warranty



POWER ANYWHERE, ANYTIME! 1300 MAC GEN (1300 622 436)

www.macfarlanegenerators.com.au info@macgen.com

MELBOURNE

136 Fairbank Road Clayton South, VIC 3169 (03) 9544 4222

SYDNEY

1 St James Place Seven Hills, NSW 2147 (02) 9899 6699

BRISBANE

31 South Pine Road Brendale, QLD 4500 (07) 3205 6333