

13kVA Maxwatt Pure Sine Wave Digital Inverter Generator

**PORTABLE & LIGHT WEIGHT
LOW NOISE 71dB | ECONOMY LOW IDLE SETTING**

Maxwatt® digital inverter generators offer the best in portable power, fuel efficiency and are super silent.

The MaxWatt MX13000iS digital inverter generator is designed to complement Home Backup Power Supply and Off-Grid Power Systems as it has a pre-installed 2-wire automatic start, run and stop control system.



**2 - WIRE
AUTO START**

FEATURES

- Pure Sine Wave Inverter Technology
- Low Noise at 71dB
- Fuel Economic Low Idle Mode
- Smart Engine Control
- Wheels & Handle for Easy Transportation
- Ideal for Home/Camping/Caravanning

MELBOURNE

136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY

1 St James Place
Seven Hills, NSW 2147
(02) 9899 8048

BRISBANE

1 South Pine Road
Brendale, QLD 4500
(07) 3205 6344

PERTH

1/85 Dixon Road
Rockingham, WA 6168
(08) 9548 7337

Specifications

Model	MX13000iS
Power Maximum	13000W
Power Rated	12000W
Voltage	240V
Amperage	50A
Outlets	1 x 15 Amp, 1 x 32 Amp, 1 x 63Amp
Displacement	744cc
Ignition	Recoil / Electric / Remote Control / 2 Wire Auto
Battery Charger	Yes
Rated Frequency	50Hz
Cont. Running Time @50% Load	9hrs
Cont. Running Time @100% Load	5.5hrs
Fuel Tank Capacity	40L
Noise Level (dB @ 75% m)	71
Total harmonic distortion (THD)	3%
Weight (kg)	164kg
Dimensions (LWH)	972 x 783 x 873mm
Manufacturer's Warranty	2 year warranty

Proudly 100% AUSTRALIAN OWNED

**MACFARLANE
GENERATORS**

ESTABLISHED 1949

POWER ANYWHERE, ANYTIME!

1300 MAC GEN (1300 622 436)

www.macfarlanegenerators.com.au

info@macgen.com

2

MELBOURNE

136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY

1 St James Place
Seven Hills, NSW 2147
(02) 9899 8048

BRISBANE

1 South Pine Road
Brendale, QLD 4500
(07) 3205 6344

PERTH

1/85 Dixon Road
Rockingham, WA 6168
(08) 9548 7337