

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE
GENERATORS**

ESTABLISHED 1949



10.8kVA Pramac Generator (P11000-AMF-3)

The Pramac P11000-AMF is designed for Automatic Mains Failure.

Low noise level, it is equipped with a reliable Diesel engine, first class components and complete instrumentation.



**THE
SILENT
POWER**



P11000-AMF 400V

FEATURES

- Low Noise Level
- Quiet Operation – 68dB
- Electric Start
- 400V 50HZ
- Genset Manual Control Panels
- Coolant Pre-heating System

MELBOURNE

136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY

1 St James Place
Seven Hills, NSW 2147
(02) 9899 6699

BRISBANE

31 South Pine Road
Brendale, QLD 4500
(07) 3205 6333

Specifications

Model	P11000-AMF-3
Frequency	50Hz
Voltage	400V
Power Factor	0.8
Standby Power LTP	10.8kVA
Continuous Power COP	10kVA
Engine Manufacturer	Yanmar 3TNV70-HGE
Starting System	Electric
Aspiration	Natural
Fuel	Diesel
Weight	325kg
Dimensions (L x W x H)	1400 x 650 x 975 mm
Fuel Tank Capacity	24L
Noise Level (dB @ 7m)	68dB
Phase	3

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE
GENERATORS**

ESTABLISHED 1949

POWER ANYWHERE, ANYTIME!

1300 MAC GEN (1300 622 436)

www.macfarlanegenerators.com.au

info@macgen.com

MELBOURNE

136 Fairbank Road
Clayton South, VIC 3169
(03) 9544 4222

SYDNEY

1 St James Place
Seven Hills, NSW 2147
(02) 9899 6699

BRISBANE

31 South Pine Road
Brendale, QLD 4500
(07) 3205 6333