

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

**MAXWATT**<sup>TM</sup>  
POWER WHEN YOU NEED IT

**MX11000iS**

# 10.5kVA Maxwatt Pure Sine Wave Digital Inverter Generator

**PORTABLE & LIGHT WEIGHT  
2-WIRE AUTO START | LOW NOISE**

Maxwatt® digital inverter generators offer the portable power and fuel efficiency, while maintaining quiet operation.

The MaxWatt MX1100iS powers sensitive equipment and is ideal for food trucks, coffee vans, markets, events, and emergency home backup. It has a rated output of 9500 watts and a maximum of 10500 watts.

It features a powerful, economical, quality 550cc 4 stroke air cooled engine, digital inverter technology with (THD<3%). Designed to complement off-grid solar systems, the MX11000iS includes a pre-installed 2-wire automatic start, run, and stop control system.



**DOUBLE  
POWER**  
WITH PARALLEL  
CONNECTIVITY



*Ideal for home backup, off grid solar, food vans, markets and events.*

## FEATURES

- Digital Inverter Technology
- Pure Sine Wave Power for Sensitive Electronic Appliances / Devices
- 4 in 1 Digital Meter
- Fuel Economic Low Idle Mode
- Engine Smart Control
- Compact and Easy to Transport

### MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

### SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 8048

### BRISBANE

1 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6344

### PERTH

1/85 Dixon Road  
Rockingham, WA 6168  
(08) 9548 7337

# Specifications

Model	MX11000iS
Maximum Wattage	10500W
Rated Wattage	9500W
Voltage	240V
Amperage	39.6A
Phase	Single
Ignition	Recoil / Electric / Remote Control / 2 Wire Auto
Battery	12V 10Ah Lead Acid
Engine	4-Stroke Air-cooled
Rated Frequency	50Hz
Displacement	550cc
Fuel Type	Petrol Unleaded
Outlets	1 x 15A IP66 / 1 x 32A IP66
Fuel Tank Capacity	30L
Noise Level (dB @ 7m)	68
Weight (kg)	103kg
Dimensions (LWH)	810 x 600 x 695mm
Manufacturer's Warranty	2 year warranty

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

**POWER ANYWHERE, ANYTIME!**  
**1300 MAC GEN (1300 622 436)**  
**[www.macfarlanegenerators.com.au](http://www.macfarlanegenerators.com.au)**  
**[info@macgen.com](mailto:info@macgen.com)**

**MELBOURNE**

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

**SYDNEY**

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 8048

**BRISBANE**

1 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6344

**PERTH**

1/85 Dixon Road  
Rockingham, WA 6168  
(08) 9548 7337