



4.3kVA RGiS Silent Inverter Generator

The 4.3kVA Subaru 'RGiS' Silent Inverter Generator is designed to run sensitive equipment like computers, televisions.

These units were used during the Melbourne Commonwealth games to run metal detectors. They are an ideal power source for motor homes or just perfect for clean power for industry specific tasks.

With its Inverter Control System (Electronic voltage control) it achieves high quality output with less fluctuation and wave distortion and allows the engine speed to be automatically adjusted in direct proportion to the load applied maximising fuel efficiency, while maintaining 240v (50 cycles) supply.

The 4.3kVA Subaru 'RGiS' Silent Inverter is Powered by 'EX' Extreme OHC engine with a 3 year warranty.

The double-wall acoustical housing-damping panels reduces both high frequency and low frequency noise. These sound attenuating materials are highly fire-resistant. A State-of-the-Art Inverter combines load-sensing electronic throttle control with improved combustion & lubrication to significantly reduce fuel consumption, plus yield a quieter, softer tone on start-up & shut-down as well as constant running.

There is very low noise as a result of inverter technology & engine management system, the engine need not work as hard to generate high levels of electrical power. Special vibration control isolators & highly efficient soft-tone muffler further reduce noise.

The high quality electrical output from a portable unit. Smooth power is comparable to public utility sources. Ideal for powering computers & equipment sensitive to voltage surges.

Designed for long running construction and rental applications, SUBARU builds the entire engine and generator together as one high quality unit.

This unit also meets the strictest environmental regulations, the U.S. Phase II, CARB Tier II, LEMA, and European emission regulations.

Features:

- High Power & Performance
- Great Reliability & Durability
- Long range fuel tank
- Easy Maintenance
- Electric Start provides easy starting
- Sound Proofing Panels - Whisper Quiet
- Low Fuel Consumption
- Excellent Cost/Performance Ratio
- 12V DC battery

Applications:


- Powering electrical equipment
- Event Hire
- Rural Farms

Industry:

- Caravaning & RV use
- Equipment Sensitive to Power Surges
- Computers & Medical Equipment
- Sensitive Instrumentation
- Emergency Stand-by
- Mobile Emergency Power
- Anywhere Power Is Needed in the Field

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE
GENERATORS**



ESTABLISHED 1949

Head Office:
136 Fairbank Road
Clayton South,
Vic 3169
Tel.: 03 9544 4222
Email: sales@macgen.com

Join us on Facebook



WWW.MACFARLANEGENERATORS.COM.AU



4.3kVA RGiS Silent Inverter Generator




Specifications

Model Number	RG4300iS
kVA	4.3
Phase	Single
Fuel Type	Petrol
Starting System	E/Start & R/Start
Watts (w)	4300
Rated Output (w)	3440
Alternator Type	Inverter
Voltage (V)	240v - 50hz
Voltage Regulation	Inverter
Battery Charger	12V
DC Output	12 - 8.3
Over Load Protector	Electronic circuit breaker
Engine Make	Subaru
Engine Type	9.0hp EX27
Engine Features	Air-cooled, 4-stroke, OHC Gasoline Engine
Fuel Tank (L)	16.0L
Running Time (Rated Output)	6.6hr
Noise Level (dB @ 7m)	62.0
Weight (kg)	74kg
Dimensions (LxWxH)	580x527x618
Manufacturer's Warranty	2 years
Engine Warranty	3 years

PROUDLY 100% AUSTRALIAN OWNED

MACFARLANE GENERATORS



ESTABLISHED 1949

Head Office:
136 Fairbank Road
Clayton South,
Vic 3169
Tel.: 03 9544 4222
Email: sales@macgen.com

Join us on Facebook



WWW.MACFARLANEGENERATORS.COM.AU