

# 10kVA Subaru **Portable Generator**

This superior 10.0kVA single phase generator The RGV's Safety design features oil sensor performance and reliability. The V-Twin de- less circuit breaker. livers magical high power with smooth, reliable torque, improved breathing at high rpm, Features and low fuel consumption, compared to conventional side-valve engines.

The RGV range of SUBARU generators, coupled with their V-Twin engines offer a host of benefits. The RGV has outstanding durable • reinforced and rugged structure with a • strong frame construction. The large safety • muffler achieves a markedly lower noise level equal to that of 5kw class. A large battery tray can carry a battery up to 260 x 170 x 205 mm (case size).

The RGV's reliability and low maintenance is ensured with the combination of highperformance Subaru OHV V-twin engine and weather-proof (IP23 level) alternator and a 3 Year Subaru engine warranty. Its easy operation electric start key-switch and starting • motor located on the front control panel, an extra large long range 44L fuel tank ensures plenty of fuel for a day's work.

offers Subaru's V-Twin engine's renowned and fuel shut-off solenoid valve and a fuse-

- Electric Start
- HD steel frame
  - 4 Wheel Kit
- **AC Voltmeter**
- AC Circuit breaker
- Oil sensor
- Extra large fuel tank with fuel gauge
- Dust proof cyclone air cleaner
- Large capacity silent muffler

- Weather Proof Outlets
- Central Lifting Bar
- Earth Leakage Switch
- Circuit Breakers
- Earth Spike & Lead

- Fire Extinguisher
- Bunding
- Safety Stop
- Battery Isolator

# **Applications**

- Powering electrical equipment
- **Event Hire**
- Rural Farms

# Industry

- Hire & Rental
- Mining & Oil
- Farm & Rural
- Backup Power
- Shires & Councils
- Government
- Medical



Head Office: 136 Fairbank Road Clayton South,

Vic 3169 Tel.: 03 9544 4222

Email: sales@macgen.com

Join us on Facebook







# 8.5kVA Crommelins Portable Generator



**Specifications** RGV12100 **Model Number** kVA 10kva **Phase** Single **Fuel Type** Petrol **Starting System** E/Start & R/Start Watts (w) 10,000w Rated Output (w) 8000w **Alternator Type** Brushtype, self exciting, 2 poles 240v - 50hz Voltage (V) Voltage Regulation **AVR Over Load Protector** Fuseless circuit breaker **Engine Make** Subaru 22.0hp EH65D **Engine Type** Air cooled, 4 stroke, V-Twin OHV **Engine Features** petrol Fuel Tank (L) 44.0L Running Time (Rated Output) 8.9hr 75db Noise Level (dB @ 7m) Weight (kg) 149kg **Dimensions (LxWxH)** 826x611x771mm **Manufacturers Warranty** 2 years **Engine Warranty** 3 years

PROUDLY 100% AUSTRALIAN OWNED



ESTABLISHED 1949

Head Office: 136 Fairbank Road Clayton South, Vic 3169

Tel.: 03 9544 4222

Email: sales@macgen.com

Join us on Facebook



WWW.MACFARLANEGENERATORS.COM.AU